

- **Connect line output converter gray wire(+)** and **gray/black wire(-)** to the right speaker output of the source unit;
- **Connect line output converter white wire(+)** and **white/black wire(-)** to the left speaker output of the source unit;
- **Connect line output converter yellow wire** to **VCC +12v**;
- **Connect line output converter black wire** to **ground**;
- **Connect line output converter blue wire** to **remote turn-on for amplifier**;
- **If there is only one stereo minus, connect both line output converter minus wires** to it;
- **The rca jacks are the output for the line output converter, step down w/adjust control pots for the desired output;**

